COMPANICS
Communication & Electronics LTD

כומפניקס תקשורת ואלקטרוניקה בע"מ
הבורסקאי 1 א.ת. סגולה, פ"ת | ספק מ. הביטחון: 83524121 | ח.פ: 512109968
03-9049004 טל' / | www.companics.co.il | sales@companics.co.il

Model Number 37020B
100V Public Address System Volume Control with 24V Relay

Features:



לצפייה באתר לחץ כאן

- PA (Public address) system use volume control with 24V relay.
- Background music system with voice alarm use attenuator with 24V relay.
- The volume controller is used to adjust the loudspeaker output in the room.
- The volume controller is used to keep same output level for one same speaker line, because the end the speaker line signal loss is rather big, so its outputs is less, thus volume controller is added to the front of the line to lower the speaker output so as to keep the similar ambient output level for the all of the speaker win the same line.
- The volume controller with 24V relay working principle: the relay from the amplifier or PA system will be input to this volume controller to override the output level to maximum when there is fire alarm or other emergency situation, by this way, some conference room even lower the volume or off the level during meeting even could hear the evacuation message during emergency.
- High level white UV-protected ABS material to integrate together with the white wall and architecture design.
- Built-in transformer to control the PA 100V line loudspeakers.
- With 4 levels of volume attenuator and one position of off.
- Surface wall mount or in-wall mounting box shall be purchased separated.

Specifications:

Item	100V Public Address System Volume Control with 24V Relay			
Model	15786	15787	15788	15789
Description	100V Volume Controller with Relay			
Rated Output	6W	30W	60W	120W
24V Relay	With 24V relay			
Line Input	100V or 70V			
Volume Step	5 steps			
Attenuation Per Step	3dB			
Total Attenuation	33dB			
Material	UV-protected ABS			
Finish	White			
Mounting Way	Surface mount or in-wall mount			
Depth	50mm	60mm		
Plate Dimension	60mm			